

REMARKS**BEST AVAILABLE COPY**

The specification has been amended to correct errors of a typographical and grammatical nature. Due to the number of corrections thereto, applicants submit herewith a Substitute Specification, along with a marked-up copy of the original specification for the Examiner's convenience. The substitute specification includes the changes as shown in the marked-up copy and includes no new matter. Therefore, entry of the Substitute Specification is respectfully requested.

The abstract has also been amended to more clearly describe the features of the present invention.

Entry of the preliminary amendments and examination of the application is respectfully requested.

To the extent necessary, applicant's petition for an extension of time under 37 CFR 1.136. Please charge any shortage in the fees due in connection with the filing of this paper, including extension of time fees, to Deposit Account No. 01-2135 (501.41076X00) and please credit any excess fees to such deposit account.

Respectfully submitted,

ANTONELLI, TERRY, STOUT & KRAUS, LLP



Carl I. Brundidge
Registration No. 29,621

DRA/CIB/jla
(703) 312-6600

REWRITTEN MARKED UP COPY**Abstract of the ~~Invention~~ Disclosure**

A packet switching system ~~that~~ arbitrates between Virtual Output Queues (VoQ) in plural input buffers, so as to grant the right of transmitting data to a crossbar switch to some of the VoQs by taking both an output data interval of a VoQ and the queue length of a VoQ as parameters, ~~wherein the~~. The system suppresses the delay time of the segment of a VoQ having a high load, thereby preventing buffers from overflowing; and, also, the system permits ~~the~~ a VoQ having a low loads load to transmit segments under no influence of the VoQ that has a high load and is just reading out the segment.

Marked-up

-1-

501.411076X00
CIBadd line
numberingRECEIVED
CENTRAL FAX CENTER

JUN 06 2006

Title of the Invention

PACKET SWITCHING SYSTEM

Background of the Invention

The present invention relates to a packet switching system having an input buffer and an output buffer (referred to as ^{an} input/output buffer packet switching system, hereinafter), particularly to ^a (the) packet switching system adopting an arbiter system.

^A Conventional input/output buffer packet switching system, which has a First-In First-Out (FIFO) memory for each input line, has a disadvantage ^{in that} where if plural packets inputted from plural input lines converge at a predetermined output path, "Head Of Line (HOL) blocking" is caused, ^{in which there is} [suffering from] only 58.6% throughput of data transfer. To avoid (the) HOL blocking, there ^{is} provided a well known method ^{in which a} ^{is provided} ^A (that has) Virtual output Queue (VoQ), for each output path at an input buffer.

The input/output buffer packet switching system, ^{associated with a crossbar switch} because ^{of} a crossbar switch (which) has no buffer, adopts ^{the} a way to arbitrate between the VoQs of input buffers, so as to prevent data on the crossbar switch from being converged. The arbitration is performed for ^{the purpose of selecting} ^{which} ^{the right} [deciding] a combination of an input port and an output port to ^{give the grant} of

-2-

(grant) is given transmitting data to some of the VoQs. Accordingly, higher throughput of data transfer of the switching system depends on efficient arbitration.

There are two ways ^{to effect} (of) arbitration for ^{selecting} (deciding) a combination of an input port and an output port: one, where arbitration is performed using the unit of a fixed-length internal packet into which variable length packets ^{have} inputted to the switch ^{and} ^{are} ^{in the form} [has] been divided; another, where, as indicated in USP 09/362,134, arbitration is performed using the unit of a fixed-length container into which plural variable length packets ^{are} packed. In this way, two units are used ^(on) ^{in the form} in the [a] switching processing; one unit, of an internal packet having a small fixed length and another unit, ^{in the form} of a container having a large fixed length.

As regards a unit used ⁱⁿ ^{carried out} (on) the processing in the switching system of the invention, the volume of data per arbitration is defined as one segment. Note that hereafter the term "segment" is also ^{used} ^a ^{to indicate} (defined) as a generic term ^(of) data to be treated inside the switch, data such as an internal packet, a packet, and a cell.

As conventional arbitration, the following three methods ^{have been} ^{are} proposed:

First, ^{these} is a method of selecting a sending queue ^a on a Round Robin basis by taking ^{into consideration} whether ^{the} a segment of VoQ exists as a parameter, as disclosed in "A Study of structuring a Large Capacity Packet

-3-

Switching Systems," Koji WAKAYAMA, et al., SHINGAKUGIHO

SSE98-160, and also disclosed in JP-A-2000-78148;

Second, ^{there} is a method of selecting sending queues by taking (a) ^{the} waiting time of the segment in ^{as} VoQ as a parameter, disclosed in "A Study of Scheduling an Input Buffer Switch and Trial manufacture thereof," Toshiyuki SUDO, et al., SHINGAKUGIHO SSE99-118; and

Third, ^{there} is a method of selecting ^{an} output data queue by taking the length of ^{the} VoQ as a parameter, ^{as} disclosed in "A Proposal of Balanced Packet Scheduling Algorithm and Performance Evaluation," SHINGAKUGIHO SSE96-56.

Each of the three methods has a problem, ^{this is} caused when ^{an} unbalanced load is ^{applied} given to the switch. Referring to Fig. 16, which is a conceptual view of an input port 30 of a 4 X 4 switch, ^{an example of} [we will explain] ^{will be explained} the problems ^{below}. In the figure, reference numbers 31-1, ³¹31-2, ³¹31-3, and ³¹31-4 ^{denote} are VoQs, each being directed ^{along} (for) its output path; a quadrangle in each VoQ represents a segment ^{the}. The ^{VoQ} 31-1 ^{has} [shows] traffic which ^{represents} [has] a higher load than ^{the} other queues; and the ^{VoQ} 31-4 ^{has} [shows] traffic which ^{represents} [has] a lower load than other queues.

In the first method of selecting a sending queue on ^a basis ^{into consideration}, by taking ^a whether a segment of VoQ exists as a parameter, if unbalanced loads are ^{applied} given to the switch, the ^{approach} Round Robin that equitably reads out segments from all VoQs permits the VoQ having ^a low load to transmit segments ^{without regard to} (under) ^a.

-4-

[no influence on] the VoQ that has^a high load and is just reading out [the]^a segment. However, ^{the} queue^a of a VoQ having^a high load is liable to be long, causing its delay time in segment transmission inside the switch to be longer than those of ^{the} other VoQs. As shown in ^{Fig. 16} [the figure], this brings about ^{an} overflow of segments at VoQ 31-1 having^a high load, and might ^{result in} ^{being abandoned} (abandon) a segment 32A.

In the second method of selecting sending queues by taking ^{the} [a] waiting time of ^a VoQ of ^{in the VoQ} the segment^a as a parameter, in the same way as the first method, ^{the} queue^a of a VoQ having^a high load is liable to be long. This ^{also} causes ^{the} [a] waiting time of the segment in ^a the VoQ^a to be long. ^{having a low load} The ^{since the} method that takes ^{the} [a] waiting time of the segment in VoQ as a parameter transmits a segment having a long waiting time in a priority manner. ^{In addition} [Under the condition], management of the waiting time of all segments needs a lot of counters, so the method is not practicable.

Therefore, in most cases^a, the second method counts the waiting time from when the segment has arrived at the top of the queue. Specifically, it adds 1 to the counter of the VoQ when the segment in the VoQ is not transmitted during one arbitration, while ^{it} resets the counter when the segment is transmitted during one arbitration. This treats both^a VoQ having^a high load and^a VoQ having^a low load in the same

-5-

^{way} (Condition), because the counter resets once the segments of the VoQ which even has ^a high load ^{and} (is) transmitted.

Thus, the delay time of the VoQ to which ^a high load is given under the unbalanced load ^{condition} finally becomes large, and thus this might ^{eliminate} (abandon) the overflow segments of the buffer.

In the third method of selecting sending queues by taking the length of the queue as a parameter, the segment can be effectively read out from ^a VoQ having ^a high load under above-said condition where ^{an} unbalanced load is ^{applied} (given) to the switch. Thus, the delay time of the segment of ^a VoQ having ^a high load ^{becomes} (comes to be) small, also preventing a buffer from overflowing. The method, however, suffers from a phenomenon called starvation, in which ^{the} ^{of a transmission right} grant ^a is not given to a segment 32B of VoQ 31-4 that has ^a low load.

Accordingly, the method might ^{result in} deteriorate ^{the} ^{of the} quality ^{of data} of data in packets, especially in both packets of voice data, which ^{are} (is) required never to be late in data transfer, and packets of important data, which ^{are} (is) required never to be abandoned in data transfer, both for keeping good quality in data.

Summary of the Invention

^{It is an object of the} (The) invention (aims) to provide a packet switching system that arbitrates between (the) VoQs to ^{select} (decide) a combination of an input port and an output port, and thereby ^{the right to} grant ~~transmit~~ data to some of the VoQs by taking both

-6-

an interval in sending a segment from ^aVoQ and ^{the} queue length of ^{the}VoQ as parameters.

According to one aspect of the invention we provide the packet switching system having: a queue length manager for managing the volume of segments queued in each VoQ per input line; an output data interval manager for managing an output data interval of the segment of each VoQ; and an arbiter-request (ARB-REQ) generator for allocating ^a level of transmission to the VoQs according to information received from the queue length manager and the output data interval manager, wherein arbitration is performed on the level ^{allowed to} assigned each VoQ so as to determine which VoQs will be ^{send}.

According to another aspect of the invention, we provide ^a packet switching system having: means for putting segment transfer interval prior to queue length in arbitration so as to determine ^aVoQ level; and means for putting queue length prior to segment transfer interval in arbitration so as to determine ^aVoQ level;

Brief Description of the Drawings

FIG. 1 is a block diagram ^{showing} (for explaining) ^{one} embodiment of a packet switching system of the present invention.

FIG. 2 is a block diagram of the structure of an ARB-REQ generator 13 and a VoQ controller 12 ^{as used in the system} of FIG. 1.

-7-

a diagram showing
FIG. 3 is ^aone example of a level assignment matrix for assigning a level to ^aVoQ by the ARB-REQ generator of FIG.

13.

a diagram showing
FIG. 4 is ^aone example (prioritizing output data interval) of the level assignment matrix for assigning the level to ^aVoQ by the ARB-REQ generator of FIG. 1.

a diagram showing
FIG. 5 is ^aone example (prioritizing queue length) of the level assigning matrix for assigning the level to ^aVoQ by ^{the} ARB-REQ generator of FIG. 1.

FIG. 6 is a block diagram of an example of the structure of an arbiter ^{as used in the system} 14 of FIG. 1.

diagram illustrating
FIG. 7 is ^aview for explaining a concept of a VoQ level matrix of the present invention.

diagram illustrating
FIG. 8 is ^aview for explaining a concept of a tournament of the present invention.

showing results
FIG. 9 is a table ^{showing} of a combination of win and defeat ^{in accordance with} of the tournament for every input and every output ^{of} the present invention.

FIG. 10 is ^aview for explaining a concept of ^alevel reassignment table ^{according to} of the present invention.

illustration
FIG. 11 is a flowchart ^(for explaining) an algorithm which the arbiter 14 of FIG. 1 performs.

is a diagram which
FIG. 12 ^{is a diagram which} illustrates processing of the arbiter 14 of FIG. 1.

-8-

FIG. 13 is a block diagram of ^{the overall} [a total] structure of another embodiment of a packet switching system of the present invention.

FIG. 14 is a graph ^{compared to} [of] indicating 99 % delay of the conventional arbiter [and] an arbiter of the present invention.

FIG. 15 is a graph of indicating queue length distribution of the conventional arbiter and the arbiter of the present invention when an unbalanced load is given.

FIG. 16 is a ^{diagram illustrating} [view for explaining] a concept of [an] overflow of ^aVoQ to which high load traffic is ^{applied} [given] and starvation of ^aVoQ to which low load traffic is ^{applied} [given].

Detailed Description of the preferred embodiments

FIG. 1 illustrates one embodiment of a packet switching system of the present invention. In the system, ARB-REQ information is transmitted to an arbiter through a separate line 18, which ^a is different from a data line for connecting ^{the} VoQ 11 and Crossbar Switch 19.

An input line processor 16-i ($i=1$ to n) extracts address information of a packet by analyzing a [packet] header of a packet which is input from an input line 103-i. An input buffer 10-i includes n VoQ11-i ^{in correspondence} to an output port [Correspondence]. An input processor 16-1 gives address information which has been extracted to a VoQ controller 12-^c

-9-

The VoQ controller 12-i gives an indication to an input buffer 10-i (so as) to write the packet in^a VoQ corresponding to the output^{according} (corresponding) to^{the} address information. In this way, the packet is written in VoQ 11-i which has been designated.

The VoQ controller 12-i manages, per VoQ 11-i, information between the volume of queuing segments and a waiting time (that is to say, an output data interval of each segment) of the segment at the top of a queue buffer. An ARB-REQ generator 13-1 assigns each level to each VoQ according to (those of)^{such} information.

Each VoQ level is collected to an arbiter 14 by a signal line 18 during one arbitration period. It is^{determined} (decided) by the arbiter 14 (to give grant) to which^{to give the grant} (of) VoQ^{the received} according to (its) information.

Grant information is transmitted to each of^{the} VoQ controllers 12-i ($i=1, \dots, n$) as ARB-ACK by a signal line 15, and, at the same time, the arbiter reflects the results of its arbitration to the structure of a path inside^{the} (a) crossbar switch. The VoQ controller 12-i informs (it to) the input buffer 10 (that)^{of} which (of) VoQ should send a segment according to its ARB-ACK information.

The segment transmitted from the input buffer 10-i is switched by (a) crossbar switch 19 and then transmitted to an output line processor 17-i. The output line processor 17-i

-10-

restructures the packet from the segment which has been received from the crossbar switch 19 and then sends it to an output line 104-i.

With reference to FIG. 2, the structures of the VoQ controller 12 and the ARB-REQ generator 13 ^{will be} described in detail. ^{by} ^{request} ^{shows} ~~At this point~~, FIG. 2 ~~employs~~ one example of ~~the~~ ~~case of~~ a 4 × 4 switch ~~size~~ for simple explanation.

The header of the packet, which has been processed in the header analyzer 401 inside the input processor 16, is transmitted to a write address (WA) generator 403 in the VoQ controller 12, ^{and the WA generator 403 determines to which VoQ 11} ~~managed~~ to write an input packet ~~to which~~ ~~VoQ 11~~ by the WA generator 403. The WA generator 403 sends memory address information to the input buffer 10 by way of a WA control signal line 412, and gives an indication of writing the packet ^{to} VoQ 11 corresponding to a destination. At the same time, the WA generator 403 transmits information of the packet which has been written in the input buffer 10 to a queue length manager 405 and an output data interval manager 406. The queue length manager 405 ^{has} a queue length counter 410 corresponding to each of ^{the} ~~all~~ VoQs inside the input buffer 10.

^{illustrates} FIG. 2 ~~gives~~ the case of a 4 × 4 switch as an example. Since four VoQs exist in the input buffer 10, the queue length manager has four queue length counters 410. The queue length manager 405 increases the length of the segment of

-11-

the input packet to the numeric value of the queue length counter 410 for the current length of the queue. The output data interval manager 406 has an output data interval counter 411 corresponding to ^{each of} one or more VoQs inside the input buffer 10. The output data interval manager 406 does nothing to the VoQ in which the packet has been input in the case where the segment has already existed. If the segment has not existed, the output data interval manager 406 gives an indication to the output data interval counter 411 corresponding to the VoQ so as to add 1 to the numeric value per arbitration period, and manages the output data interval time. In other words, the numerical value which the output data interval counter 411 shows indicates ^{that} how long the segment has not been transmitted from corresponding VoQs.

A read address (RA) generator 404, according to ARB-ACK information transmitted from the signal line 15, ^{to the input buffer} transmits, through a signal line 413, information ^{indicating} ~~to send~~ ^{is to be sent} from which VoQ the segment ^{to the input buffer}. At the same time, the read address (RA) generator 404 transmits information of the segment which is read out from the input buffer 10 to the queue length manager 405 and the output data interval manager 406 as well. The queue length manager 405 decreases the queue length counter 410 corresponding to ^{the} VoQ which has transmitted out ^a ~~the~~ segment to the crossbar switch 19. Further, the output data interval manager 406 resets

-12-

the value of the output data interval counter 411 corresponding to ^{that} (the) VoQ.

Information of the queue length manager 405 and of the output data interval manager 406 is transmitted to the ARB-REQ generator 13 by way of a signal line 414. The ARB-REQ generator 13 has an ARB-REQ generating part 409 corresponding to each queue inside the input buffer 10. Respective ARB-REQ generating parts 409-1 to ⁴⁰⁹409-4 assign some level to the corresponding queue according to information received from the ARB-REQ generator 13. When the level is assigned to the queue, a VoQ level assignment matrix 416 is referred ^{to}. For the VoQ level assignment matrix 416, it is possible for a user to tune the arbiter in accordance with the characteristics of the traffic ^{is} which (are) input to the node thereof. The level of each VoQ which has been created in the ARB-REQ generator is transmitted to the arbiter 14 by way of the signal line 18.

FIG. 3 shows one embodiment of the VoQ level assignment matrix 416. The level assignment matrix has a segment transfer interval 71 (in a ^{along the} horizontal axis and the number of segments queued in VoQ (in a ^{along the} vertical axis 72. The longer an output data interval time is and the more the number of segments queued in ^{the} VoQ is, the bigger the level assigned to ^{the} VoQ is. The level assignment matrix is

-13-

calculated from a queue length (the number of segment in VoQ) and the segment transfer interval.

By assigning the level to the queue in this way, it comes to be possible to send, within ^{an arbitrarily set} (a) delay time (for setting) (arbitrarily), the packet which has entered into the switch.

The time for sending the packet from the queue of ^aVoQ having a high load is longer than that of ^aVoQ having a low load. Thus, a high level is assigned to ^aVoQ in which the number of segments stored in the queue is big, ^{whereby transmission} (and thus) grant is given thereto in a priority manner. In other words, this level indicates information of the degree of priority in obtaining grant.

Since the packet is transmitted within a delay time which is set arbitrarily by way of ^aVoQ having ^alow load, it functions to increase the VoQ level if the transmitting interval becomes long.

The VoQ level L is obtained from the following expression.

$$L = \frac{1}{\ln\left(\frac{M - a \cdot t}{b \cdot s} \times e\right)} \times 15$$

-14-

where, M: time out, t: output segment interval, s: the number of segments at the present time, a: output data coefficient, b: queue length coefficient.

When $(M-a \cdot t)/b \cdot s \leq 1$ is attained, the VoQ level attains the maximum value. When the VoQ level has reached the maximum value, it is indicated that the VoQ thereof has reached [to such] a condition [as] having a high possibility of obtaining a grant.

M is a value which is defined from both a delay time that can arbitrarily be set by the switch and one arbitration time. M is also a value for deciding both the maximum value of segment transfer interval 71 in ^{the} level assignment matrix and the maximum value of the number of segments 72 queued in ^a VoQ. Where T is the delay time which is required by the switch and ^{is} determined arbitrarily, t_a is a time for one arbitration time, n is the number of input ports of the switch. M can be obtained by the following expression.

$$M = \frac{T}{t_a} - n$$

T/t_a can define the number of times [of performing] arbitration ^{is performed} during the delay time T, which can be defined arbitrarily. On the assumption that the levels of all VoQs attain the maximum values at the same time, until the grant

-15-

is given, ^a λ VoQ, to which the time for maximum n arbitration will be waited, appears. Therefore, in order to transmit the segment within the delay time which is arbitrarily defined, even if ^a λ VoQ has only one segment, a VOQ level takes ^{the} maximum ^{value} when the output data interval becomes $T/ta-n$.

As ^{apparent} [shown] from the level assignment matrix shown in FIG. 3, since the VoQ level becomes high as the output data interval ^{becomes} [turns to be] large in ^a λ VoQ having only one segment, it is not necessarily concluded that the segments are not transmitted until the maximum delay time is requested.

The level assignment matrix in FIG. 3 is limited to time out $M = 20$, $a = 1$, and $b = 1$. By changing an output data interval coefficient ^a and a queue length coefficient b , it is possible for them to be changed to arbitration which regards the output data interval as important and arbitration which regards ^{the} (a) queue length as important.

When the packet switching system of the present invention is employed in a place where, for example, a lot of voice data ^{is processed which is} required never to be late in data transfer, (should be processed) ^{the} setting is changed so as to suppress the delay time as much as possible where such data are queued in ^a λ VoQ having low load traffic.

^{More specifically} (a) Concretely, setting the value of the output data interval coefficient a to 1 or more permits the VoQ in which the segments are not yet filled to get a large level within

-16-

a short output data interval. FIG. 4 shows the condition of the VoQ level assignment matrix at the time of defining the value of the output data interval coefficient a as 2. When the level of the matrix in FIG. 4 is compared with the level assignment matrix of FIG. 3, the VoQ level already becomes large when the output data interval of the segment is small. Thus, it is also possible for ^aVoQ having ^a(the) low load to transmit the segment in a short delay time.

On the contrary, when the packet switching system of the present invention is employed in a place where a lot of data ^{is processed which is} required never to be abandoned in data transfer, ^{the} [should] ^{be processed}, though the delay time of ^aVoQ having ^a(the) low load traffic lengthens slightly, it is preferable to suppress an overflow of a buffer by outputting the segments from ^aVoQ having ^a(the) high load traffic in a priority manner. In such a case, by defining the value of the queue length coefficient b as ^a(the) value greater than 1, it is permitted to assign the VoQ level which acts in response sensitively to a change of the length of the queue. When ^a(the) high load is applied, the length of the queue ^{becomes} [turns to be] long. FIG. 5 exemplifies the condition of the level assignment matrix at the time of assigning the queue length coefficient as 2. When the level assignment matrix is compared with the level assignment matrix of FIG. 3, large levels are found in places in which the number of the segments of VoQ is small.

-17-

Therefore, for VoQ in which the length of the queue becomes longer, it is possible to prevent, ^aVoQ, in which the length of the queue becomes longer, from ~~(the)~~ buffer overflowing by making it easy to give ^agrant by ^{assigning}~~(giving)~~ a larger level as soon as ^{possible}~~(earliest)~~.

Further, where the output data interval is not considered at all and it is desired that arbitration is performed using only the length of the queue, it ^{becomes}~~(comes to)~~ possible by defining the value of the output data interval coefficient a as 0.

All of the VoQ levels calculated by a numeric expression 1 are rounded off and they are expressed in the level assignment matrix as integers. Further, when $M - a \cdot t < b \cdot s$ or $M \leq a \cdot t$ is attained, they become ~~(the)~~ values other than $0 < L \leq 15$. However, when such a situation occurs, since it is expressed that the VoQ level already exceeds the maximum level 15, the level 15 is given to ^aVoQ to which the values other than $0 < L \leq 15$ are given by this expression.

Information of the level per VoQ is collected to arbiter 14 from each ARB-REQ generator.

FIG. 6 is a block diagram of an embodiment of the arbiter 14. In all VoQ level ~~collectors~~ ¹²¹, information of the level of all VoQs is collected.

FIG. 7 ^{illustrates a} ~~(expresses the)~~ condition ~~(of)~~ ^{for} all VoQs to which requests have been made as of arbitrary points of time. The

-18-

columns of the matrix express~~es~~ an output line number 131, and the rows thereof express~~es~~ an input line number 132. For example, in the case where an input line number is 1 and an output line number is 1, the level, which is assigned to VoQ 11-1-1 of an input buffer 10-1 of FIG. 1, is stored. Further, a "0" 133 of the matrix has the same VoQ level and ^a(the) level smaller than "0" is assigned to an empty portion.

In this ^{example} condition, giving grant to ^aVoQ having an output line number 4 in an input line number 2 and ^aVoQ having an output line number 2 in an input line number 4 obtain the best combination of inputs and outputs. In order to give grant to ^aVoQ efficiently all the time, a tournament for each ^{the} inputs and a tournament for each of ^{the} outputs are performed.

FIG. 8 ^{shows} (is a view of) a concept of tournament processing. In FIG. 8, numerals represent the level of ^aVoQ which is a member of the same input line number or output line number. In FIG. 8, ^{when} [though] there are two VoQs having the same levels, (in such a case) it is made not ^{preferable for} to win either one, but ^{to win} (to win) for all VoQs having the same level^s. This is to give grant efficiently as shown in FIG. 7.

This tournament processing is performed for each of ^{the} input line directions and for each of ^{the} output line directions in (an) every input line tournament processor 122-1 and (an) every output line tournament processor 122-2, and then ^aVoQ is selected, which has the highest VoQ level (the request

-19-

[of] transmitting is the highest among their line numbers) among them.

As [the] result of the tournament, a win/defeat combination 141 [of] FIG. 9 is capable of being considered for an input line direction and an output line direction. The level reassignment part 124 evaluates information of each VoQ level by reducing to [4] levels, 0 to 3, according to a level reassignment table 61 [of] FIG. 10. *an example of which is shown in*

VoQs which have been reevaluated into [4] levels, 0 to 3, are picked up sequentially from VoQs of the level 3 in a selector 125 of a VoQ having the same level. Grant is given to a VoQ which has been picked up herein by a Round Robin selection in a grant assignment part 126.

Since it is not possible to give grant in the same arbitration period from both a VoQ to which grant is given and a VoQ which is a member of the same input line number or the same output line number, grant is taken away in a grant deprivation part 127.

Information of a VoQ, grant of which has been deprived, is notified to all VoQ level collectors 121 by way of a signal line 123. From this information, the tournament is performed once more among VoQs, grant of which has not been deprived at all, and then the levels thereof are reevaluated. Then, in the same way as the aforementioned processing description, a VoQ having level 3 is picked up by way of a same level VoQ

-20-

selector 125, and then grant is given to the VoQ by a grant assignment part through the Round Robin selection. By repeating such a repetitive operation, it is possible to create the best combination of input line and output line.

Since it is not possible to give grant at the same time in the same arbitration period from ^aVoQs that are members of the same input line number or the same output line number as VoQs having grant in the aforementioned process, the grant deprivation part 127 deprives grant from the VoQs.

Information of ^aVoQ, ^{the} grant of which has been deprived, is ^{communicated} notified to the same level VoQ selector 125 by way of a signal line 129. The same level VoQ selector 125 picks up ^aVoQ having level 2 still having ^agrant and then gives ^agrant by the grant assignment part through the Round Robin selection.

Then, by way of the same process as giving ^agrant to ^aVoQ having ^alevel 2, grant is given to ^aVoQ having ^alevel 1. Grant is also given to ^aVoQ with the level 0 having ^agrant to be transmitted next.

Grant information is changed to ARB-ACK information by an ARB-ACK generator 128, and then ^{it is} transmitted to the RA generator 404 of the VoQ controller 12 by way of the signal line 15. The RA generator 404 transmits the segment-transmitting signal 413 to ^{the}VoQ, according to ^{the}ARB-ACK information. At the same time, VoQ information for sending the segment is ^{communicated} notified to the queue length manager

-21-

405 and the output data interval manager 406. The queue length manager 405 decreases the number of transmitted segments from the value of the queue length counter 410, which manages the number of segments of ^{the} VoQ to which ^{the} grant has been given. In the output data interval manager 406, the value of the sending out interval counter 411, which manages the output data interval of ^{the} VoQ to which ^{the} grant has been given, is reset.

FIG. 11 is a flowchart of a sequential process ^{performed by} ~~of~~ the aforementioned arbiter 14. ^A ~~The~~ tournament is performed ~~to~~ ^{for} the VoQ levels which have been collected from each of the input buffers with respect to the input and the output (S81). The VoQ levels thereof are reevaluated using the levels of 3 to 0 in order of highly requested output data for each VoQ (S82-1 to -4). First of all, VoQs of the level 3 are picked up by way of the same level VoQ selector 125 (S83). Grant is given to them through ^{selection} ~~(the)~~ Round Robin ^(S83-1) (it may be considered to adopt 2DRR (Mamoru TAKAHASHI, et al., "Improvement of Packet-Priority-considered-Packet-Switch having Input Queue corresponding to each Output Port," SHINGAKUGIHOU SSE97-13) and the like, which has a pointer in order to maintain the state of being equal as this Round ^{selection} Robin). Since it is not possible to transmit the segment at the same time ⁱⁿ ~~(as)~~ the same arbitration period from ^{the} VoQ for

-22-

the same input and the same output as ^{the} VoQ to which ^{a grant} ~~the~~ VoQ has ^{been} given, ^a grant of ^{the} VoQ is deprived (S83-2).

In the present embodiment, in order to improve ^{the} efficiency of the arbiter, not to give ^a grant to ^a VoQ having level 2, but the level of VoQ, to which grant is not given, is back to the level of 0 to 15 before reevaluating, the tournament is performed once more, and then reevaluation of the level (S84) is performed. The more this process is repeated, the more the combination of the queues selected by arbitration ^{are} ~~is~~ closed to the most suitable one.

As a result of reevaluating, ^a grant is given to ^a VoQ having level 3 (S83-1). Grant of ^a VoQ, which has the same combination of input lines and output lines as the VoQ obtaining ^a grant, is cancelled (S83-2).

Subsequently, ^a VoQ having ^{the} level 2 is picked up (S85), grant is given (S85-1), and then ^{the} grant of ^a VoQ which has the same combination of input lines and output lines as ^{the} VoQ to which grant has ^{been} given is canceled (S85-2).

Subsequently, ^a VoQ having ^a level 1 is picked up (S86), grant is given (S86-1), and then grant of VoQ which has the same combination of input lines and output lines as ^{the} VoQ to which grant has ^{been} given is canceled (S86-2).

At last, if there is ^a VoQ having ^a grant at the level 0, grant is given by way of the Round Robin selection (S87). In this way, ^{the process} ~~it~~ is ended to give ^a grant to the combination

-23-

of all of the inputs and the outputs, and then the process of arbitration ^{is} [has been] finished.

FIG. 12 ^{shows} [is] the results of processing in accordance with the flowchart of FIG. 11. This figure indicates arbitration of the 4 X 4 switch. It is possible to express the VoQ levels, which have been collected in all VoQ level collectors 121, visually ^{way of} in a matrix 21 [way]. The rows of the matrix indicate the input line number, and the columns indicate the output line number. This matrix shows that, for example, in the matrix 21, the VoQ level for the input line number 3 and the output line number 1 is 10.

The tournament of FIG. 8 is performed for each of the input lines and the output lines, and, thereafter, ^{the} aforementioned reevaluation is performed in FIG. 10. [A] ^{the} matrix 22 indicates the results thereof.

The matrix 23 shows that ^aVoQ having level 3 has been selected from the matrix 22 and grant has been given thereto by way of the Round Robin selection. Since grant cannot be given to ^aVoQ which has the same input line number or output line number as ^aVoQ to which grant has been given at the same arbitration period, grant is deprived therefrom. The symbol "x" of the matrix 24 indicates that grant has been deprived.

Next, The level of ^aVoQ to which grant has not yet been given is back to the level of ^aVoQ which has been created in the ARB-REQ generator. A matrix 25 indicates the matrix

-24-

which has already been converted. Once more, the tournament and reevaluation of the levels are performed.

A matrix 26 indicates the result thereof. In the matrix 26, grant is given to VoQ having level 3. At this point, grant is given to VoQ having the input line number 2 and the output input number 4.

A matrix 27 indicates that grant has been given thereto. Grant is deprived from ^aVoQ which has the same input line number and the output line number as VoQ to which ^agrant has been given.

A matrix 28 indicates that ^agrant has been deprived therefrom. Next, grant is given to ^aVoQ having level 2.

A matrix 29 indicates that grant has been given thereto.

In the case [of being] ^{with reference to} explained [in] FIG. 6, since grant has been given to all of the combinations of inputs and outputs in accordance with the aforementioned processes, (a) ^{the} series of arbitrations has terminated. For the case other than that, there may be a case where a process of giving ^agrant to ^aVoQ having ^alevel 1 and ^a[the] level 0 is required. In such a case, grant is given in accordance with the flowchart of

✓ FIG. 11.

^{shows} FIG. 13 [is] another embodiment of the packet switching system of the present invention. In ^{this} [the] embodiment, by giving ARB-REQ information to a header portion of the

-25-

segment without using another line, it is transmitted to an arbiter via ^{an} in-channel.

The ^{differences between this embodiment and} ~~points~~ different from the packet switching system of FIG. 1 are that ARB-REQ information is ^{first} (once) transmitted to an ARB-REQ assignment part 111 by way of a signal line 118 and then to the arbiter 14 by giving ARB-REQ information 114 to the header portion of a segment 113, and that the arbiter 14 is included inside the crossbar switch 19.

In the same way as the embodiment of FIG. 1, ARB-REQ information is collected in the arbiter 14, and then it is decided ^{to give the grant} [to give] to which VoQ from ARB-REQ information. Then, grant information is assigned to a header 116 of a switched segment 115 as ARB-ACK from the arbiter by way of the signal line 129. Grant information is collected in an ARB-ACK collection part 112, and then ^{it is} transmitted to the VoQ controller 12 by way of a signal line 119. The VoQ controller 12 instructs an input buffer ^{from which VoQ} to transmit the segment ~~(from)~~ ^(which VoQ).

The advantageous point of this method is that it is possible to ^{simplify} ~~make simple~~ the structure of ^{the} ~~(a)~~ hardware, since the number of ~~(the)~~ signal lines can be decreased, because it is not required to prepare the signal line for the arbiter.

FIGS. 14 and 15 show results of the simulation of a queue information management arbiter of the present invention and an arbitration method (referring to Koji

-26-

WAKAYAMA, et al., "A Study of structuring a Large Capacity Packet Switching Systems," SHINGAKUGIHO IN98-160) for performing the Round Robin^{selection} by judging the presence of the segment of^a VoQ under the same condition. It is supposed that the condition of the simulation is a 4×4 input output crossbar switch having^{four} (the) input lines^{four} (number 4) and (the) output lines^{number 4}.

FIG. 14 shows a distribution graph of an average delay time of the conventional arbiter and the proposed arbiter of the present^{invention} (application) at the time of having uniform traffic. The vertical axis 92^{denotes} Delay (Segment), and the horizontal axis 91^{denotes} (has) Load Rate (%). The higher the load of a line is, the bigger the volume of the delay of the conventional arbiter is. However, it is possible for the proposed arbiter to suppress the delay time from increasing.

Even for uniform traffic, if the load of the line becomes higher, the traffic condition tends to be unbalanced. Therefore, the proposed arbiter, which takes both^{the} output data interval and^a queue length of^a VoQ as parameters, can suppress the delay time better than the conventional arbiter, which^{considers only} (takes) whether the segment exists as a parameter.

FIG. 15 shows the results of the simulation of the delay distribution of^a VoQ having^a low load traffic and^a VoQ having^a high load traffic when traffic having^a (the) load higher

-27-

than others is given to one input line among ^{from} [4] input lines. The vertical axis 102 ^{denotes} [is] Probability (Delay time > d), and the horizontal axis 101 ^{denotes} [is] Delay (segment).

Quadrilateral plots ^{denote} [express] the delay distribution of the input port having traffic of the higher load, and triangle ^{or} plots ^{denote} [express] the delay distribution of the input port having traffic of the lower load.

As shown from the delay distribution of ^aVoQ having traffic of the higher load, the proposed arbiter suppresses the delay time better than the conventional type arbiter. The length of the queue of ^aVoQ having [traffic of] the higher traffic is longer than that of ^{the} other VoQs. The proposed ^{by} [type] of performing arbitration, taking the length of the queue as a parameter tends to give much ^{consideration} ^a [grant] to ^aVoQ having long queue length. This can suppress the delay time of ^aVoQ having traffic of ^a [the] higher load.

On the other hand, though an impact is given to ^aVoQ having traffic of ^a [the] low load by said effect, the switching system of the present invention can suppress the effect ^{to} ^a VoQ having ^a low load traffic because it takes ^{the} output data interval as a parameter.

Since the length of the queue is managed, it is possible to perform highly effective switching even when unbalanced loads are ^{applied} ^a [given] to the switch. It is possible to suppress the delay time of ^aVoQ effectively, to which

-28-

traffic of ^athe ^{applied}high load is ^agiven. Further, it is possible to transmit ^athe ^{an}segment without giving ^athe effect to ^aVoQ to which traffic of ^athe ^{applied}low load is ^agiven.

Even for ^aVoQ to which traffic of ^athe ^{applied}low load is ^agiven, it is possible for ^aVoQ level to take the maximum level when the time predetermined by a user arrives. Thus, it ^{becomes}comes (to be) easy to remain undefeated in the input direction and the output direction for the tournament of next processing, and thus it ^{becomes}comes to possible to attain the maximum level when the level is reevaluated. Therefore, it ^{becomes}comes to be easy for its VoQ to obtain grant of the segment. Therefore, it ^{becomes}comes to be possible to prevent starvation of ^aVoQ to which traffic of ^athe ^{applied}low load is ^agiven.

By employing the present invention, it is possible to provide ^{an}the ^{that is}arbiter capable of managing any of ^athe balanced loads or ^athe unbalanced loads.

**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☐ BLACK BORDERS
- ☐ IMAGE CUT OFF AT TOP, BOTTOM OR SIDES
- ☐ FADED TEXT OR DRAWING
- ☐ BLURRED OR ILLEGIBLE TEXT OR DRAWING
- ☐ SKEWED/SLANTED IMAGES
- ☐ COLOR OR BLACK AND WHITE PHOTOGRAPHS
- ☐ GRAY SCALE DOCUMENTS
- ☒ LINES OR MARKS ON ORIGINAL DOCUMENT
- ☐ REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY
- ☐ OTHER: _____

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.